



## Duo(GVR-3003) Dual Channel Linear Voltage Regulator

Duo(GVR-3003) regulator of the helicopter was developed as a linear regulator with a dedicated Gyro, RC cars, planes, boats, etc. are designed to be used as general purpose.

Unlike conventional regulator, it will be installed between Battery – Receiver, Receiver – Servo or receiver – Gyro and it can be easily and securely operated without switch.

### Specifications

- Input voltage : 6 to 10 Volts (5 to 8 cell NiCd/MH or 2cell LiFe/Po)
- Output voltage : 5.2V, 6.0V
- Output current : 3A(Continuous), MAX 10A(@6V,30sec)
- Size : 10mm(H) x 23mm(W) x 40mm(L)
- Weight : 10g (Excluding cables)
- Components : Main unit 1EA, RX cable 2EA

### Features

- ◆ Using a high quality LDO controller as a Linear Regulator essentially switching noise does not occur and for the load on voltage stability and transient response characteristics and the current supply capacity is excellent.
- ◆ High Power Devices Parallel Design maximum output 10A(@30sec) and has been promoting safety.
- ◆ Set the jumper connectors using the output voltage of 5.2V 6.0V can be selected.
- ◆ Exclusive Gyro regulator which is accurate and reliable regulator indicates Rudder response characteristics as well.
- ◆ Compact size and weight, as well as RC helicopters, airplanes, cars, boats, etc. can be used as the main regulator, the former distance.

### Technical support & Customer Service

Contact your dealer or e-mail us at address below for questions about our products or Customer Service.

E-mail : [master@gryphon.co.kr](mailto:master@gryphon.co.kr)

### **GRYPHON**

673-39 Manchon1 Suseng-gu  
Daegu, Korea  
TEL +82 53 783 1796  
FAX +82 53 289 0724  
ULR : <http://www.gryphon.co.kr>  
<http://www.gryphon-mail.com>

©Copyright 2009 by Gryphon. All rights reserved. Printed in Korea.